

eX-SM1110 Managed Gigabit Ethernet Extenders

Managed Long Range LAN Extender



- Extends 10/100/1000Base-T Ethernet up to 10,000 feet (3 KM) over 2-wire 24 AWG twisted pair
- High-Speed – up to 200+ mbps aggregate bandwidth
- Transparent operation for all Ethernet protocols including 802.1Q VLAN packets and IP video compression schemes
- Advanced features - Link Pass-Through, Interlink Fault Feedback, Auto-MDIX and Loopback
- **Manage via SNMP, CLI - Telnet/SSH, Internet browser, or PerleVIEW Central Management Platform**

10/100/1000 Ethernet Extenders allow you to extend Ethernet services beyond the general IEEE 802.3 limits of 328ft / 100m using **any existing copper wiring** previously used in alarm circuits, E1/T1 circuits, RS-232, RS-422, RS-485, CCTV and CATV applications. For environments where the **10/100/1000 LAN is being extended** and **network security is critical**, Perle offers **Managed Gigabit Ethernet Extenders** that support all **authentication, authorization and accounting (AAA) security** services used in corporate networks, including TACACS+, RADIUS, LDAP, Kerberos, NIS and RSA. To further protect ID's and passwords from someone 'snooping' on the network, Perle Managed Ethernet Extenders provide **secure management sessions** by supporting **SSH, SNMPv3, Telnet and HTTPS**. These types of features are used when managing your corporate firewalls, switches and routers. This is why Perle makes them available in the **eX-SM1110 Managed Ethernet Extender**.

These simple and effective point to point Ethernet Copper Extenders are perfect for commercial buildings, residential units, hospitality environments and remote offices ... **anywhere you need the ability to securely configure, monitor and manage long range Ethernet communication links** between separated LANs or LAN devices (i.e. PCs, digital sensors, VoIP phones, WiFi Access Points, IP cameras and more).

You will also appreciate how easy it is to set up the **eX-SM1110** with an intuitive Web Manager GUI and multiple methods of access. And, with support for IPv6, Perle Managed Ethernet Extenders provide organizations with investment protection to meet this rapidly growing standard. For high density applications check out the **eX-CM1110 Managed Fast Ethernet Extender Modules**.

10/100/1000 Ethernet Extenders are also available as unmanaged standalone models with support for **Commercial Temperature ranges** and **Extended Temperature ranges**.

eX-SM1110 Managed Gigabit Ethernet Extender Features

Perle's advanced features such as Link Pass-Through, Interlink Fault Feedback, and Loopback allow Network administrators to "see everything" for more **efficient troubleshooting and less on-site maintenance**. These cost and time saving features, along with a **lifetime warranty and free worldwide technical support**, make **Perle eX-SM1110 Managed Ethernet Extenders** the smart choice for IT professionals. This Ethernet Extender also has many **NERC CIP** compliance features.

Extend Ethernet over twisted pair

Extend an Ethernet link over category 5e, 6 and 7 cabling up to 10,000 feet (3 km)

Extend Ethernet over Coaxial cable

Extend an Ethernet link over 75 ohm coaxial cable

High-Speed Performance

Utilizes second generation VDSL2 technology (ITU-T Recommendation G.993.) . When operating under "Profile 30a", Perle Ethernet extenders can provide an aggregate VDSL line rate capability of over 200 mbps. Actual distance and performance may vary depending on the type / gauge and condition of the wire used.

Plug and Play operation

Perle Ethernet Extenders will automatically configure your VDSL interlink connection. The CO/CPE peer association will be determined automatically by the Ethernet Extender. No need to set CO / CPE VDSL pairing.

Once a connection is made, both ends will automatically adjust relevant VDSL parameters to optimize the level of bandwidth possible across the copper link.

Link Pass-Through

With Link Pass-Through the state of the 10/100/1000Base-T Ethernet connection is "passed through" the VDSL link to the 10/100/1000Base-T Ethernet connection on its remote peer. A managed switch on the remote end can then report the state (link up or link down) to its network management system so that any errors can be detected and recovered early.

Competitive Ethernet extenders without this feature will never detect or report any error conditions.

Interlink Fault Feedback

Similar to the Link Pass-Through feature, a loss of VDSL link will drop the 10/100/1000 Ethernet ports on each end until the link recovers.

Auto-Negotiation

The Ethernet Extender supports auto negotiation on the 10/100/1000Base-T interface.

Auto-MDIX

Auto-MDIX (Automatic Medium-Dependent Interface crossover) detects the signaling on the 10/100/1000 Ethernet RJ45 interface and determines the type of cable connected (straight-through or crossover) and automatically adopts a compatible pinout.

Fixed Speed and Duplex

Some Ethernet equipment require a fixed speed and duplex be used or cannot auto-negotiate. By disabling Auto-Negotiation on the Ethernet Extender, a fixed speed of 10, 100 or 1000 mbps as well as Full or half Duplex can be configured through DIP switches.

VLAN

Transparent to tagged VLAN (802.1Q) packets.

Transparent to IP Video compression protocols

Fully transparent to such IP video compression schemes such as MPEG-4, H.264 and MJPEG.

VDSL Configuration

- Enable/Disable port
- Set Port Name – Up to 8 characters
- Set Role : Auto (Default) ,Local (CO), Remote (CPE)
- Set Rate/Reach : High-Speed (default) , Long-Range
- Set Symmetry : Asymmetric, Symmetric (default)
- Set Low Bandwidth Alarm – SNMP trap
- Select VDSL profile
- Select Signal to Noise Ratio
- Select upstream/downstream data rate

Quality of Service

- Bandwidth Allocation via rate limiting
- IEEE 802.1P tagged frame priority control
- IEEE 802.1P priority tag remapping
- IP TOS (Type of Service) priority for IPV4 Diffserv or IPV6 traffic class frames
- Congestion Service Policy through WQF (Weighted Fair Queuing) or Strict Priority Queuing (default)

VLAN Tagging

- Default – Transparent to VLAN frames
- Enable discarding of tagged frames
- Enable discarding of untagged frames
- Untag – Removes any existing tag
- Insert Tag – Insert (if original frame is untagged) or replace (if original frame is tagged) the VLAN ID and priority with the configured default VLAN ID and priority tag.
- Insert Double tag (Q in Q) – Append an additional tag using the configured default VLAN ID and priority.

Unknown Multicast Frame filtering

When enabled, Multicast frames with an unknown destination address are not allowed to egress the port.

Unknown Unicast Frame filtering

When enabled, Unicast frames with an unknown destination address are not allowed to egress the port.

Unidirectional Ethernet

When enabled, provides the ability to restrict port to one-way traffic flow. Used in applications such as unidirectional video broadcasting as well as providing security for Ethernet connections in accessible public areas.

Configuration Mode selection

Select whether to use the on-board DIP switches or the management software for mode selection.

Auto-MDIX

Can manually set Auto or MDIX on the copper port via on-board strap or via the management software. Auto-MDIX (automatic medium-dependent interface crossover) detects the signaling on the UTP interface to determine the type of cable connected (straight-through or crossover) and automatically configures the connection when enabled. With Auto-MDIX enabled, either a straight-through or crossover type cable can be used to connect the Ethernet Extender to the device on the other end of the cable.

Converter Information

- User configurable Ethernet Extender name
- User configurable VDSL-Interlink port name
- User configurable copper port name
- Hardware revision number
- Firmware version number

DIP switch settings

View hardware DIP switch settings.

10BaseT Extended Distance

Normal/extended – default Normal. By configuring as “extended”, the 10baseT receiver sensitivity is increased providing the possibility of a 10BaseT connection greater than 100m.

Copper Port Status

- Port Enabled (Yes/No)
- Link Status (Up/Down)
- Auto Negotiation Settings (Disabled, Complete or In Progress)
- Resolved as crossover MDI or MDIX type

VDSL Port Status

- Port Name
- Connector Type
- Link State
 - Idle
 - Handshake
 - Training
 - Up
- Loopback status
- Remote Loopback (loopback status of VDSL peer)
- Role : Local (CO) , Remote (CPE)
- Current VDSL Profile

Control

- Reset
- Reset to factory default
- Reset Statistical counters
- Update firmware
- Loopback mode. (On/Off)
- Upload/download configuration

Detailed port statistics

To assist in troubleshooting links, an extensive list of ingress and egress counters for both copper and VDSL ports are available. These statistics can be viewed locally via the management module or from a central SNMP NMS on the network.

Pause (IEEE 802.3xy)

Pause signaling is an IEEE feature that temporarily suspends data transmission between two devices in the event that one of the devices becomes overwhelmed. The Ethernet Extender supports pause negotiation on the 10/100Base-TX copper connection.

Remote Loopback

The Ethernet Extender is capable of performing a loopback on the copper VDSL Interlink port.

eX-SM1110 Advanced Management Features

Enterprise and carrier-grade security is available through the support of strong authentication systems such as TACACS+, RADIUS and LDAP. Secure in-band access is assured via SNMPv3, SSH CLI and secure HTTPS Internet browser. This Ethernet Extender also has many **NERC CIP** compliance features.

SNMP

- Full read/write capabilities via central SNMP servers and **PerleVIEW**
- Send SNMP traps (up to 4 servers)
- SNMPv3, V2C and V1
- SNMPv3 – encryption and authentication for both management and trap support
- RFC1213 MIB II
- Proprietary MIB provided

Telnet / SSH CLI access

In-band command line access via Telnet or **SSH application**

Internet Browser access

- Fast and intuitive graphical web interface for use with common internet browsers such Internet Explorer, Mozilla Firefox and Safari
- HTTP or secure HTTPS
- **PerleVIEW Central Management Platform**

Console port CLI access

Out-of-band command line access via Cisco compatible RJ45 serial console port using common “rolled” CAT5 cable.

Console port can be enabled (default) or disabled

Concurrent management sessions

Run multiple management sessions simultaneously for multiple users

Inactivity timeout

Protect secure management sessions by setting an inactivity timeout value

Alert event reporting

Alert level events are stored in the local event log and sent as:

- SNMP traps to up to 4 servers
- SYSLOG messages to a SYSLOG server
- Email to user defined email address

Advanced IP feature set

- IPV4 and IPV6 address support
- DHCP
- DNS
- Dynamic DNS
- NTP
- TFTP
- Telnet
- SSH V2 and V1
- HTTP
- HTTPS

Advanced Management User Authentication with primary and secondary server support

- TACACS+
- RADIUS
- LDAP
- Active Directory via LDAP
- RSA Secure ID-agent or via RADIUS authentication
- Kerberos
- NIS

Advanced Management User Authorization and Accounting

- TACACS+
- RADIUS

Encryption

- AES (256/192/128), 3DES, DES, Blowfish, CAST128, ARCFOUR(RC4), ARCTWO(RC2)
- Hashing Algorithms: MD5, SHA-1, RIPEMD160, SHA1-96, and MD5-96
- Key exchange: RSA, EDH-RSA, EDH-DSS, ADH
- X.509 Certificate verification: RSA, DSA

Access Control List

An access control list can be created which can filter out only those workstations that are authorized to access the management resources. Filter on IP and/or Ethernet MAC addresses

Network Services Filter

Enable only those network services on the management module that are allowed on your network (Telnet, SSH, HTTP, HTTPS, SNMP)

Firmware download

Update the latest level firmware via TFTP or **PerleVIEW**

Specifications

Lifetime limited warranty	Reach, RoHS and WEEE Compliant	HTSUS Number: 8517.62.0020	UNSPSC Code: 43222608	ECCN: 5A992
----------------------------------	---------------------------------------	--------------------------------------	---------------------------------	-----------------------



CCATS Number:
G134373

Management Module Indicators / reset

Power	- Blinking green during startup cycle - Steady green: module has power and is ready - Red : error
ALM	Red alarm indicator activated when an alert event occurs
LKC	Green indicator indicating an active Ethernet link. Blinking indicates RX and TX of data
100/1000	- Green - 1000 Mbps link - Yellow - 100 Mbps link - Off - 10 Mbps or no Link
Reset button	Recessed pinhole button resets module

Ethernet	
Port	1 port RJ45 – 10/100 Base-TX - Shielded
Auto-MDIX	Auto-MDIX enables proper operation with either straight-through or crossover cabling
Distance	Distance up to 100 meters (328 feet) as per IEEE 802.3
Maximum Frame Size	1522 bytes
VDSL – Interlink	
RJ45, BNC, Terminal Block	Ethernet Extenders must be connected in pairs using unconditioned wire. Circuits that run through signal equalization equipment are not permitted. TIP and RING are polarity insensitive. Surge suppression of 400 volts between TIP and RING. Choice of RJ45, BNC or terminal block models for VDSL link connector: • RJ45 – RING pin 4, TIP pin 5 (TIA 568 A/B) • BNC – Coaxial 50 and 75 ohm cable with BNC connector • Terminal Block – 2 position screw connectors for use with twisted pair telephone, alarm or serial cabling between 19 (0.9 mm) and 26 AWG (0.44 mm).

VDSL2 Line Rate/Reach

Actual distance and rates experienced will depend on condition and gauge of wire used. This Rate/Reach table applies to 24 AWG (0.5 MM) twisted pair wiring on RJ45 (RJ) and terminal block (TB) models

High Speed Asymmetric

Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	101	92
1000	305	101	63
1500	457	90	38
2000	610	62	24
2500	762	55	10
3000	914	42	5
3500	1000	35	3

High Speed Symmetric

Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	101	101
1000	305	85	101
1500	457	62	47
2000	610	60	29
2500	762	44	14
3000	914	30	7
3500	1000	29	4

Long Reach Symmetric

Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	53	44
1000	305	53	43
2500	762	39	18
4000	1219	25	4
5500	1676	17	1.9
7000	2134	8	2.3
7500	2286	7	2.2
8000	2438	5	2.2
Long Reach Asymmetric			
Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	78	16
1000	305	78	16
2500	762	55	10
4000	1219	31	0.8
5500	1676	20	0.6
7000	2134	11	0.6
7500	2286	10	0.6
8000	2438	8	0.6

Indicators	
Power / TST	This green LED is turned on when power is applied to the Ethernet Extender. Otherwise it is off. The LED will blink when in Loopback test mode.
CO - Local	Ethernet Extender is operating in CO VDSL mode
CPE - remote	Ethernet Extender is operating in CPE VDSL mode
ILNK	Indicates Link Status and activity on the Interlink (VDSL) port
ETH	Indicates link status and activity on Ethernet port.
Switches – On-board PCB	
Rate/Reach	Two switches enable the user to select the right balance between speed and distance for their environment.
Signal to Noise Ratio	Selectable Signal to Noise Ratio (SNR) of 6dB or 9dB. The higher SNR number provides better impulse noise protection but lowers performance.
Auto-Negotiation (802.3u)	• <i>Enabled (Default)</i> - The Ethernet Extender uses 802.3u Auto-negotiation on the 10/100/1000Base-T interface. It is set to advertise full duplex. • <i>Disabled</i> - The Ethernet Extender sets the port according to the position of the speed and duplex switches.
Link Mode	• <i>Standard (Default)</i> - The 10/100/1000Base-T link remains active independent of the state of the Ethernet link on its remote peer. • <i>Link Pass-Through</i> - the state of the 10/100/1000Base-T Ethernet connection is “passed through” or propagated across the VDSL link to the 10/100/1000Base-T Ethernet link on its remote Ethernet Extender peer. This enables a managed switch to report the state of the remote device to its network management system.
Interlink Fault Feedback	• <i>Enabled</i> - A loss of VDSL link will drop the 10/100 Ethernet port on each end until the link recovers • <i>Disabled (Default)</i> - The state of the VDSL link is not propagated to the 10/100/1000Base-T port

Loopback	• <i>Enabled</i> - The VDSL interlink will perform a loopback function, retransmitting all received Ethernet frames back to its peer. • <i>Disabled (Default - Up)</i>
Set Ethernet Speed	When Auto-Negotiation switch is disabled, fixed speed can be set at 100 (Default) or 10
Set Ethernet Duplex	When Auto-Negotiation switch is disabled, Duplex can be set at Full (Default) or Half
Power	
Input Voltage	12 vDC (nominal)
Current	560ma @ 12 vDC
Power Consumption (Watts)	6.7
Power Connector	5.5mm x 9.5mm x 2.1mm barrel socket
AC Adapter	100-240v AC, regulated DC adapter included
Environmental Specifications	
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	minimum range of -25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing
Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output (BTU/HR)	22.86
MTBF (Hours)*	221,305 Hours w/o adapter 156,656 Hours w/ adapter <i>Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>

Packaging	
Shipping Weight	1.2 Kg, 2.6 lbs
Shipping Dimensions	200 x 300 x 70 mm, 7.9 x 11.8 x 2.8 inches
Regulatory Approvals	
Emissions	- FCC Part 15 Class A, EN55022 Class A - CISPR 32:2015/EN 55032:2015 (Class A) - EN61000-3-2
Immunity	CISPR 35/EN 55035
Electrical Safety	- UL/EN/IEC 62368-1 - CAN/CSA C22.2 No. 62368-1 - UL 60950-1 - IEC 60950-1(ed 2); am1, am2 - EN 60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013 - CE

Product List



eX-1SM1110-RJ - Gigabit Ethernet IP-Managed Stand-Alone Ethernet Extender - 1 port
10/1001000Base-T (RJ-45). RJ45 Interlink (VDSL2) connector

Power Cord & Part Number(s)

USA	UK	EU	SA	AUS	None
06004134	06004131	06004132	06004135	06004136	06004138



eX-1SM1110-BNC - Gigabit Ethernet IP-Managed Stand-Alone Ethernet Extender - 1 port
10/1001000Base-T (RJ-45). BNC (Coax) Interlink (VDSL2) connector

Power Cord & Part Number(s)

USA	UK	EU	SA	AUS	None
06004144	06004141	06004142	06004145	06004146	06004148



eX-1SM1110-TB - Gigabit Ethernet IP-Managed Stand-Alone Ethernet Extender - 1 port
10/1001000Base-T (RJ-45). 2-pin Terminal Block Interlink (VDSL2) connector

Power Cord & Part Number(s)

USA	UK	EU	SA	AUS	None
06004154	06004151	06004152	06004155	06004156	06004158

Related Accessories

Power Supplies



UK Extended
Temperature 12VDC
/ 24W power adapter
for Perle Device
Servers, Media

04030671



EU Extended
Temperature 12VDC
/ 24W power adapter
for Perle Device
Servers, Media

04030672



USA Extended
Temperature 12VDC
/ 24W power adapter
for Perle Device
Servers, Media

04030674



South Africa
Extended
Temperature 12VDC
/ 24W power adapter
for Perle Device
Servers, Media

04030675



Australia Extended
Temperature 12VDC
/ 24W power adapter
for Perle Device
Servers, Media

04030676

Accessories



DIN Rail Mounting Kit for 4 & 8 port IOLAN desktop models, all Stand-Alone Media Converters and all Stand-alone Ethernet Extenders. Two of these brackets are required for the 8 port STS8-D model.

04030840



Standalone media converter wall / rack mount bracket

05059999