

# eX-S1110 Gigabit Ethernet Extenders

## 10/100/1000 Ethernet Copper Extender



- Extends 10/100/1000Base-T Ethernet up to 10,000 feet (3 KM) over 2-wire 24 AWG twisted pair
- High-Speed – up to 200+ mbps aggregate line rate
- Transparent operation for all Ethernet protocols including 802.1Q VLAN packets and IP video compression schemes
- One or four 10/100/1000 Ethernet ports
- Advanced features: Link Pass-Through\*, Interlink Fault Feedback\*, Plug and Plan, Auto-MDIX and Loopback

When you need to extend Ethernet services beyond the general IEEE 802.3 limits of 328ft / 100m, and new fiber cabling is cost prohibitive, **Ethernet Extenders** are the perfect solution. Perle Ethernet Extenders **transparently extend** up to four 10/100/1000 **Ethernet connections across copper wiring**. Use **single twisted pair (CAT5/6/7) or any existing copper wiring** previously used in alarm circuits, E1/T1 circuits, RS-232, RS-422, RS-485, CCTV and CATV applications.

These simple and effective point to point Ethernet Copper Extenders are perfect for commercial buildings, residential units, hospitality environments, connecting a remote office or private-network backbone to a corporate LAN ... anywhere you need Ethernet communication links between separated LANs or LAN devices (i.e. PCs, digital sensors, VoIP phones, WiFi APs, IP cameras and more).

Perle’s advanced features such as Link Pass-Through\*, Interlink Fault Feedback\*, and Loopback allow Network administrators to “see everything” for more efficient troubleshooting and less on-site maintenance. These cost and time saving features, along with a lifetime warranty and free worldwide technical support, make **Perle Ethernet Extenders** the smart choice for IT professionals. **eX-S1110 Ethernet Extenders** are also available with support for **Extended Temperature ranges, managed networks with AAA security and high density applications**.

## eX-S1110 Gigabit Ethernet Extender Features

### Extend Ethernet over twisted pair

Extend an Ethernet link over category 5e, 6 and 7 cabling up to 10,000 feet (3 km)

### Extend Ethernet over Coaxial cable

Extend an Ethernet link over 75 ohm coaxial cable

## High-Speed Performance

Utilizes second generation VDSL2 technology (ITU-T Recommendation G.993.) . When operating under “Profile 30a”, Perle Ethernet extenders can provide an aggregate VDSL line rate capability of over 200 mbps. Actual distance and performance may vary depending on the type / gauge and condition of the wire used.

## Plug and Play operation

Perle Ethernet Extenders will automatically configure your VDSL interlink connection. The CO/CPE peer association will be determined automatically by the Ethernet Extender. No need to set CO / CPE VDSL pairing.

Once a connection is made, both ends will automatically adjust relevant VDSL parameters to optimize the level of bandwidth possible across the copper link.

## Link Pass-Through\*

With Link Pass-Through the state of the 10/100/1000Base-T Ethernet connection is “passed through” the VDSL link to the 10/100/1000Base-T Ethernet connection on its remote peer. A managed switch on the remote end can then report the state (link up or link down) to its network management system so that any errors can be detected and recovered early.

Competitive Ethernet extenders without this feature will never detect or report any error conditions.

## Interlink Fault Feedback\*

Similar to the Link Pass-Through feature, a loss of VDSL link will drop the 10/100/1000 Ethernet ports on each end until the link recovers.

## Auto-Negotiation

The Ethernet Extender supports auto negotiation on the 10/100/1000Base-T interface.

## Auto-MDIX

Auto-MDIX (Automatic Medium-Dependent Interface crossover) detects the signaling on the 10/100/1000 Ethernet RJ45 interface and determines the type of cable connected (straight-through or crossover) and automatically adopts a compatible pinout.

### Fixed Speed and Duplex

Some Ethernet equipment require a fixed speed and duplex be used or cannot auto-negotiate. By disabling Auto-Negotiation on the Ethernet Extender, a fixed speed of 10, 100 or 1000 mbps as well as Full or half Duplex can be configured through DIP switches.

### VLAN

Transparent to tagged VLAN (802.1Q) packets.

### Transparent to IP Video compression protocols

Fully transparent to such IP video compression schemes such as MPEG-4, H.264 and MJPEG.



### Power Strain Relief strap

A strain relief strap is provided to ensure a solid and secure power connection to the Ethernet Extender. Ideal for areas that may be exposed to vibration.

### Loopback

When enabled, will perform a loopback on the copper VDSL Interlink.

\*Available on 1 port models.

Specifications				
<b>Lifetime limited warranty</b>	<b>Reach, RoHS and WEEE Compliant</b>	<b>HTSUS Number:</b> 8517.62.0020	<b>UNSPSC Code:</b> 43222608	<b>ECCN:</b> 5A991
				
Ethernet				
Port	<b>eX-1S1110</b> 1 port RJ45 – 10/100/1000 Base-T - Shielded		<b>eX-4S1110</b> 4 port RJ45 – 10/100/1000 Base-T - Shielded	

Auto-MDIX	Auto-MDIX enables proper operation with either straight-through or crossover cabling
Distance	Distance up to 100 meters (328 feet) as per IEEE 802.3
Maximum Frame Size	1522 bytes
VDSL – Interlink	
RJ45, BNC, Terminal Block	<p>Ethernet Extenders must be connected in pairs using unconditioned wire. Circuits that run through signal equalization equipment are not permitted. TIP and RING are polarity insensitive. Surge suppression of 400 volts between TIP and RING. Choice of RJ45, BNC or terminal block models for VDSL link connector:</p> <ul style="list-style-type: none"> <li>• RJ45 – RING pin 4, TIP pin 5 (TIA 568 A/B)</li> <li>• BNC – Coaxial 50 and 75 ohm cable with BNC connector</li> <li>• Terminal Block – 2 position screw connectors for use with twisted pair telephone, alarm or serial cabling between 19 (0.9 mm) and 26 AWG (0.44 mm).</li> </ul>

**VDSL2 Line Rate/Reach**

Actual distance and rates experienced will depend on condition and gauge of wire used. This Rate/Reach table applies to 24 AWG (0.5 MM) twisted pair wiring on RJ45 (RJ) and terminal block (TB) models

High Speed Asymmetric			
Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	101	92
1000	305	101	63
1500	457	90	38
2000	610	62	24
2500	762	55	10
3000	914	42	5
3500	1000	35	3

High Speed Symmetric			
Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	101	101
1000	305	85	101
1500	457	62	47
2000	610	60	29
2500	762	44	14
3000	914	30	7
3500	1000	29	4



  

Long Reach Symmetric			
----------------------	--	--	--

Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	53	44
1000	305	53	43
2500	762	39	18
4000	1219	25	4
5500	1676	17	1.9
7000	2134	8	2.3
7500	2286	7	2.2
8000	2438	5	2.2
Long Reach Asymmetric			
Reach (Distance)		VDSL Rate (Mbps)	
feet	meters	Downstream	Upstream
500	152	78	16
1000	305	78	16
2500	762	55	10
4000	1219	31	0.8
5500	1676	20	0.6
7000	2134	11	0.6
7500	2286	10	0.6
8000	2438	8	0.6

**Power**
**Input Supply Voltage**

9 - 30 vDC, unregulated (12 vDC Nominal)

Current	<b>eX-1S1110</b> 350 mA	<b>eX-4S1110</b> 500 mA
Power Consumption	<b>eX-1S1110</b> 4.2 watts	<b>eX-4S1110</b> 6 watts
Power Connector	5.5mm x 9.5mm x 2.1mm barrel socket and 2 pin terminal Block	
		
Power Adapter		
Universal AC/DC adapter	100-240v AC, regulated 12V DC adapter included	
Indicators		
Power / TST	This green LED is turned on when power is applied to the media converter. Otherwise it is off. The LED will blink when in Loopback test mode.	
CO - Local	Ethernet Extender is operating in CO VDSL mode	
CPE - remote	Ethernet Extender is operating in CPE VDSL mode	
LINK	Indicates Link Status and activity on the Interlink (VDSL) port	
ETH	Indicates link status and activity on Ethernet port(s).	
Switches		
Access	All switch settings are accessible through a side opening in the chassis	
		
Rate/Reach	Two switches enable the user to select the right balance between speed and distance for their environment.	

Signal to Noise Ratio	Selectable Signal to Noise Ratio (SNR) of 6dB or 9dB. The higher SNR number provides better impulse noise protection but lowers performance.	
Auto-Negotiation (802.3u)	<ul style="list-style-type: none"> <li>• <i>Enabled (Default)</i> - The Ethernet Extender uses 802.3u Auto-negotiation on the 10/100/1000Base-T interface. It is set to advertise full duplex.</li> <li>• <i>Disabled</i> - The Ethernet Extender sets the port according to the position of the speed and duplex switches.</li> </ul>	
Link Mode	<p><b>eX-1S1110</b></p> <ul style="list-style-type: none"> <li>• <b>Standard (Default)</b> – The 10/100/1000 Base-T link remains active independent of the state of the Ethernet link on its remote peer.</li> <li>• <b>Link Pass-Through</b> - the state of the 10/100/1000 Base-T Ethernet connection is “passed through” or propagated across the VDSL link to the 10/100/1000 Base-T Ethernet link on its remote Ethernet Extender peer. This enables a managed switch to report the state of the remote device to its network management system.</li> </ul>	<p><b>eX-4S1110</b></p> <p>N/A</p>
Interlink Fault Feedback	<p><b>eX-1S1110</b></p> <ul style="list-style-type: none"> <li>• <b>Enabled</b> – A loss of VDSL link will drop the 10/100/1000 Ethernet port on each end until the link recovers.</li> <li>• <b>Disabled (Default)</b> - The state of the VDSL link is not propagated to the 10/100/1000 Base-T port</li> </ul>	<p><b>eX-4S1110</b></p> <p>N/A</p>
Loopback	<ul style="list-style-type: none"> <li>• <b>Enabled</b> - The VDSL interlink will perform a loopback function, retransmitting all received Ethernet frames back to its peer.</li> <li>• <b>Disabled (Default - Up)</b></li> </ul>	



Set Ethernet Speed (Port 1)	When Auto-Negotiation switch is disabled, fixed speed can be set to 100 (Default) or 10	
Set Ethernet Duplex (Port 1)	When Auto-Negotiation switch is disabled, Duplex can be set to Full (Default) or Half	
Environmental Specifications		
Operating Temperature	0°C to 50°C (32°F to 122°F)	
Storage Temperature	minimum range of -25°C to 70°C (-13°F to 158°F)	
Operating Humidity	5% to 90% non-condensing	
Storage Humidity	5% to 95% non-condensing	
Operating Altitude	Up to 3,048 meters (10,000 feet)	
Heat Output (BTU/HR)	<b>eX-1S1110</b> 14.3 BTU/HR	<b>eX-4S1110</b> 20.5 BTU/HR
MTBF (Hours)*	<b>eX-1S1110</b> <ul style="list-style-type: none"> <li>• Without power adaptor: 468,351 Hours</li> <li>• With power adaptor: 289,015 Hours</li> </ul>	<b>eX-4S1110</b> <ul style="list-style-type: none"> <li>• 365,542 Hours</li> <li>• 207,212 Hours</li> </ul>
	<i>Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>	
Mounting		
Din Rail Kit	Optional	
Rack Mount Kit	Optional	
Product Weight and Dimensions		
Weight	<b>eX-1S1110</b> 0.3 kg, 0.66 lbs	<b>eX-4S1110</b> 0.47 kg, 1.04 lbs

Dimensions	<b>eX-1S1110</b> 120 x 80 x 26 mm, 4.7 x 3.1 x 1.0 inches	<b>eX-4S1110</b> 130 x 115 x 26 mm, 5.1 x 4.5 x 1.0 inches
Packaging		
Shipping Weight	<b>eX-1S1110</b> 0.55 kg, 1.2 lbs	<b>eX-4S1110</b> 0.75 kg, 1.7 lbs
Shipping Dimensions	170 x 260 x 70 mm, 6.7 x 10.2 x 2.8 inches	
Regulatory Approvals		
Emissions	<ul style="list-style-type: none"> <li>• FCC Part 15 Class A, EN55022 Class A</li> <li>• CISPR 32:2015/EN 55032:2015 (Class A)</li> <li>• EN61000-3-2</li> </ul>	
Immunity	CISPR 35/EN 55035	
Electrical Safety	<ul style="list-style-type: none"> <li>• UL/EN/IEC 62368-1</li> <li>• CAN/CSA C22.2 No. 62368-1</li> <li>• UL 60950-1</li> <li>• IEC 60950-1(ed 2); am1, am2</li> <li>• EN 60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013</li> <li>• CE</li> </ul>	

## Product List



**eX-1S1110-RJ - Gigabit Ethernet Stand-Alone Ethernet Extender** - 1 port  
 10/100/1000Base-T (RJ-45). RJ45 Interlink ( VDSL2 ) connector

### Power Cord & Part Number(s)

USA	UK	EU	SA	AUS	None
06003534	06003531	06003532	06003535	06003536	06003538



**eX-1S1110-BNC - Gigabit Ethernet Stand-Alone Ethernet Extender - 1 port**  
 10/100/1000Base-T (RJ-45). BNC ( Coax ) Interlink ( VDSL2 ) connector

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003544	06003541	06003542	06003545	06003546	06003548



**eX-1S1110-TB - Gigabit Ethernet Stand-Alone Ethernet Extender - 1 port**  
 10/100/1000Base-T (RJ-45). 2-pin Terminal Block Interlink ( VDSL2 ) connector

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003554	06003551	06003552	06003555	06003556	06003558



**eX-KIT11-S1110-RJ - Gigabit Ethernet Extender Kit - 1 pair of eX-1S1110-RJ Gigabit Ethernet Extenders**

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003834	06003831	06003832	06003835	06003836	06003838



**eX-KIT11-S1110-BNC - Gigabit Ethernet Extender Kit - 1 pair of eX-1S1110-BNC Gigabit Ethernet Extenders**

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003844	06003841	06003842	06003845	06003846	06003848



**eX-KIT11-S1110-TB - Gigabit Ethernet Extender Kit - 1 pair of eX-1S1110-TB Gigabit Ethernet Extenders**

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003854	06003851	06003852	06003855	06003856	06003858



**eX-4S1110-RJ - Gigabit Ethernet Stand-Alone Ethernet Extender - 4 port**  
 10/100/1000Base-T (RJ-45). RJ45 Interlink ( VDSL2 ) connector

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003714	06003711	06003712	06003715	06003716	06003718



**eX-4S1110-BNC - Gigabit Ethernet Stand-Alone Ethernet Extender - 4 port**  
 10/100/1000Base-T (RJ-45). BNC ( Coax ) Interlink ( VDSL2 ) connector

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003724	06003721	06003722	06003725	06003726	06003728



**eX-4S1110-TB - Gigabit Ethernet Stand-Alone Ethernet Extender - 4 port**  
 10/100/1000Base-T (RJ-45). 2-pin Terminal Block Interlink ( VDSL2 ) connector

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003734	06003731	06003732	06003735	06003736	06003738



**eX-KIT44-S1110-RJ - Gigabit Ethernet Extender Kit - 1 pair of port eX-4S1110-RJ Gigabit Ethernet Extenders**

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003894	06003891	06003892	06003895	06003896	06003898



**eX-KIT44-S1110-BNC - Gigabit Ethernet Extender Kit - 1 pair of port eX-4S1110-BNC Gigabit Ethernet Extenders**

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003904	06003901	06003902	06003905	06003906	06003908



**eX-KIT44-S1110-TB - Gigabit Ethernet Extender Kit** - 1 pair of port eX-4S1110-TB Gigabit Ethernet Extenders

**Power Cord & Part Number(s)**

USA	UK	EU	SA	AUS	None
06003914	06003911	06003912	06003915	06003916	06003918

**Related Accessories**

**Power Supplies**



UK Extended Temperature 12VDC / 24W power adapter for Perle Device Servers, Media

**04030671**



EU Extended Temperature 12VDC / 24W power adapter for Perle Device Servers, Media

**04030672**



USA Extended Temperature 12VDC / 24W power adapter for Perle Device Servers, Media

**04030674**



South Africa Extended Temperature 12VDC / 24W power adapter for Perle Device

**04030675**



Australia Extended Temperature 12VDC / 24W power adapter for Perle Device Servers, Media

**04030676**

**Accessories**



DIN Rail Mounting Kit for 4 & 8 port IOLAN desktop models, all Stand-Alone Media Converters and all Stand-alone Ethernet Extenders. Two of these brackets are required for the 8 port STS8-D model.

**04030840**



Standalone media converter wall / rack mount bracket

**05059999**